

## Frequently Asked Questions:

### Memory:

**Q. How many hours of pulse oximetry can be stored in memory for download?**

**A.** Up to 70 hours of pulse rate and SpO2 data may be stored. nVISION software may be used to retrieve and analyze the data. Analog download data to PC via data transfer cable.

**Q. What happens to the data in memory after 70 hours have been stored?**

**A.** The 7500 will continue recording in a “looping” fashion, replacing the oldest data.

**Q. How is the memory cleared?**

**A.** Patient memory can be cleared using the Model 7500's **Setup** mode. Press the **Limits** button to enter **Setup** mode, and use the **Limits** button again to scroll through the device's options until **Memory Clear** is displayed. Select “Yes” or “No” using the **Plus (+)** or **Minus (-)** buttons to clear patient memory, and then confirm your selection using the **Limits** button.

### Battery:

**Q. How many hours of battery life can I expect?**

**A.** Sixteen hours minimum when fully charged.

**Q. How long does it take to recharge the battery pack?**

**A.** Approximately four hours if the battery pack is completely discharged and the system is not in use. The battery pack continuously charges while the device is plugged into AC power. Charging will be longer if the system is in use.